

- There still might be deviation between the actual value of some data and the value provided, if there is any doubt or dispute, please refer to our final explanation.
- Please contact the supplier or customer service if there is any problem occurred when using the device.
- We are not liable for any loss caused by the operations that do not comply with the Manual.
- All trademarks, registered trademarks and the company names in the Manual are the properties of their respective owners.
- Please visit our website or contact your local service engineer for more information.
- If there is any uncertainty or controversy, please refer to our final explanation.

1 Introduction

1.1 General

This series of products comply with the HDCVI standard and support the transmission of video and control signal over coaxial cable. They produce video signal with megapixel resolution and require XVR device that comply with the HDCVI standard to achieve high speed, long distance and zero lag transmission of the signal. They are applicable to cover the high definition monitoring needs for locations like financial center, telecom site, supermarket, hotel, government, school and factory.

1.2 Features

- 720p series support over 800 meter real-time transmission of video and control signal from RG59 cable, for 1080p, 4M and 4k series, the distance is 500 meter.
- Effectively enhanced detection accuracy with quadruple digital sensor.
- Detection range: 110°, detection distance: 2m-10m.
- Adaptive to environmental change with digital temperature compensation technology.
- Auto switch from vivid color images by day and black-and-white images at night with ICR.
- Provide clear IR imaging by adjusting IR light to moving objects with smart IR.
- Configuring devices easily with OSD menu.
- IP67 rated.

2 Design

2.1 Dimension




Figure 2-1 (unit: mm [in])

2.2 Front View




Figure 2-2

No.	Name
①	Alarm indicator light
②	Lens
③	PIR lens

Table 2-1

Foreword

General

This user's manual (hereinafter referred to be "the Manual") introduces the functions, installation and operations of the camera.

Safety Instructions


The following categorized signal words with defined meaning might appear in the Manual.

Signal Words	Meaning
DANGER	Indicates a high potential hazard which, if not avoided, will result in death or serious injury.
WARNING	Indicates a medium or low potential hazard which, if not avoided, could result in slight or moderate injury.
CAUTION	Indicates a potential risk which, if not avoided, may result in property damage, data loss, lower performance, or unpredictable result.
ELECTRICITY	Indicates dangerous high voltage. Take care to avoid coming into contact with electricity.
LASER BEAM	Indicates a laser radiation hazard. Take care to avoid exposure to a laser beam.
ESD	Electrostatic Sensitive Devices. Indicates a device that is sensitive to electrostatic discharge.
TIPS	Provides methods to help you solve a problem or save you time
NOTE	Provides additional information as the emphasis and supplement to the text.

About the Manual

- The Manual is for reference only. If there is inconsistency between the Manual and the actual product, the actual product shall govern.
- All the designs and software are subject to change without prior written notice. The product updates might cause some differences between the actual product and the Manual. Please contact the customer service for the latest program and supplementary documentation.

2.3 Cable



For more information about cable ports, see Table 2-2; for the operation method of ⑥(DIP switch), see Table 2-3.

No.	Port Name	Function
①	DC 12V Power Input	Inputs DC 12V power. Please be sure to supply power as instructed in the manual. CAUTION Device abnormality or damage could occur if power is not supplied correctly.
②	Video Output	Connects to XVR to output video signal.
③	Audio Input	Connects to sound-pick-up devices to receive analog audio signal.
④	DIP Switch	Dial switches to change output mode. Switch up indicates "ON", switch down indicates "OFF."

Table 2-2

Switch1	Switch2	Output Mode
OFF	OFF	CVI
ON	ON	CVBS
ON	OFF	AHD
OFF	ON	TVI

Table 2-3

NOTE

- Cable type might vary with different cameras, the actual product shall prevail.
- PIR is available only on CVI mode.

3 Detection Range

The horizontal detection range of the sensor is 110 degree, see Figure 3-1.




Figure 3-1 (unit: m)

The vertical detection distance of the sensor is 2 to 10 meters, see Figure 3-2.




Figure 3-2 (unit: m)

4 Installation

CAUTION

- Make sure the mounting surface is strong enough to hold at least three times of the camera weight.
- Do not install the camera to the place exposed to direct sunlight.
- Do not install the camera to the place with drastic wind speed changes.
- Do not install the camera to the place with excessive temperature.
- Do not install the camera to the place with obstructions within the detection range.
- Do not install the camera to the place with massive metal objects around.
- The following figure is for reference only, the actual product shall prevail.

For the installation diagram and item list, see Figure 4-1 and Table 4-1.




Figure 4-1

No.	Item	No.	Item	No.	Item
①	Device	②	Self-tapping screw	③	Bracket
④	Expansion bolt	⑤	Mounting surface		

Table 4-1

- Step 1** Find the mounting template sticker from the accessory pack and stick it to the mounting surface⑤. Drill screw holes (and the cable outlet hole if it needs to go through the mounting surface) on the mounting surface as indicated on the mounting template.
- Step 2** Different approaches required according to different mounting surfaces.
 - For masonry mounting surface, insert expansion bolts④ from the accessory pack in the screw holes.
 - For wooden mounting surface, expansion bolts are optional.
- Step 3** Adjust the location of the bracket③ according to cable outlet requirement (top out or side out), then pull the cable out through mounting surface or the side cable tray. Align the screw holes on the bracket③ to those on the mounting surface, then put in and fasten the supplied self-tapping screws② to attach the device① to the mounting surface.
- Step 4** Connect the camera to power source and the XVR device, and the live view screen will be displayed.
- Step 5** Adjust the view of the camera, aim the lens to the ideal angle, see Figure 4-2.




Figure 4-2

5 Configuration

Power up the camera and connect it to XVR device with coaxial cable, then the live view screen is displayed. The following instructions will guide you to configure your camera.

NOTE

The number of the coaxial port on XVR will display at the lower left corner of the live view window to indicate the corresponding camera.

5.1 Opening Main Menu

Step 1 In the live view screen interface, right-click anywhere on the screen. The shortcut menu is displayed. See Figure 5-1.




Figure 5-1

Step 2 Click **Main Menu**. The Main Menu interface is displayed. See Figure 5-2.




Figure 5-2

NOTE

Right-click anywhere on the screen to return to the previous menu until you goes back to the live view screen interface.

5.2 Setting PIR

Step 1 In the Main Menu interface (Figure 5-2), select **ALARM > VIDEO DETECT > Motion Detect**. The Motion Detect setting interface is displayed. See Figure 5-3.




Figure 5-3

Step 2 In the Motion Detect setting interface, you can configure the PIR settings.

- In the **Channel** list, select the camera that you want to configure according to the coaxial port number.
- Enable **MD** function.
- Enable **PIR** function.

Step 3 Click **Apply** to save the settings.

NOTE

- Alarm would be issued only when PIR and MD are both triggered.
- If PIR is not enabled, system would be using regular MD only.

5.3 Setting Audio Input

NOTE

Audio signal acquisition is available on select models.

Step 1 In the Main Menu interface (Figure 5-2), select **CAMERA > ENCODE > Encode**. The Encode setting interface is displayed. See Figure 5-4.




Figure 5-4

Step 2 In the **Channel** list, select the camera that you want to configure according to the coaxial port number.

Step 3 In the Main Stream column, click **More Setting**. The More Setting interface is displayed. See Figure 5-5.




Figure 5-5

Step 4 In the More Setting interface, you can configure the audio settings.

- Enable **Audio Encode** function.
- In the **Audio Format** list, leave to the default.
- In the **Audio Source** list, select **HDCVI**.

Step 5 Click **Save** to save the settings. The Encode setting interface is displayed.

Step 6 In the Encode setting interface (Figure 5-3), click **Apply**.

5.4 Operating OSD Menu

Step 1 In the live view screen interface, right-click within the live view window of the camera that you want to configure. The shortcut menu (Figure 5-1) is displayed.

Step 2 Click **PTZ**. The PTZ setting interface is displayed. See Figure 5-6.




Figure 5-6

Step 3 Click **+** to see more options. See Figure 5-7.




Figure 5-7

Step 4 Click **+**. The MENU OPERATION panel is displayed. See Figure 5-8. The OSD menu of the corresponding camera is displayed on the live view screen.




Figure 5-8

For the function of the buttons in the MENU OPERATION panel, see Table 5-1.

Button	Function	Button	Function
Enter	Enter or confirm an item	↑, ↓	Select item
Cancel	Exit OSD menu	←, →	Change item value

Table 5-1

If there is '↑' as the value of an OSD item, click **Enter** to go to the next level of this item. Click **Return** to go back to the previous level. Clicking **Cancel** is to exit OSD menu without saving the modifications.

NOTE

- Interfaces of different XVR might vary, the actual product shall prevail.
- The OSD menus of different cameras might vary, the actual product shall prevail.

Appendix 1 Maintenance

CAUTION

In order to maintain the image quality and proper functioning of the device, please read the following maintenance instructions carefully and hold rigid adherence.

Maintaining Lens and Mirror Surface

Do not touch the image sensor directly. The lens and mirror surface are covered with antireflection coating, which could be contaminated or damaged and result in lens scratches or haze image when being touched with dust, grease, fingerprints and other similar substances. Dust and dirt could be removed with air blower, or you can wipe the lens gently with soft cloth that moistened with alcohol.

Maintaining Device Body

Device body can be cleaned with soft dry cloth, which can also be used to remove stubborn stains when moistened with mild detergent. To avoid possible damage on device body coating which could cause performance decrease, do not use volatile solvent such as alcohol, benzene, diluent and so on to clean the device body, nor can strong, abrasive detergent be used.

Appendix 2 Specifications

Character	Specification
Detection Method	Quadruple PIR
Detection Range	110°, 2m-10m, 5 zones
Alarm indication	Red LED light
Pet immunity	≤ 18kg
Installation height	2.2m ~ 2.5 m
Installation mode	Wall-mounting
Operating temperature	-10°C ~ 50°C
Camera operating humidity	< 95%